

IFC200

USB DATA LOGGER INTERFACE



Features

- Compatible With Most MadgeTech Data Loggers
- "Plug and Play" - No Driver Installation Required
- Blue, Green and Red LED Indicators
- Reduced noise with longer sensor leads

MadgeTech's IFC200 interface cable communicates between stand alone data loggers and the MadgeTech software. Through this interface, loggers can be started, stopped or downloaded.



The IFC200 has been redesigned, and is now "plug and play". It can be directly connected to a computer without installing any drivers and is compatible with Windows XP SP3, Windows Vista (32 and 64 bit), and Windows 7 (32 and 64 bit) operating systems. The improved IFC200 can now operate at up to 500 Volts RMS relative to the computer's earth ground when attached.

The IFC200 is equipped with communication LEDs, that provide a quick indication of the device status. The blue light illuminates when the device is plugged in and successfully recognized by Windows. The red light flashes when data is sent, and the green light flashes when data is received.



IFC200 SPECIFICATIONS*

Operating Environment: -20°C to +50°C (-4°F to +122°F)

Materials: Polycarbonate Enclosure

Dimensions: Enclosure: 1.9" x 0.69" x 0.32 (48.4mm x 17.5mm x 8.1mm)

Dimensions: Cable: 6' included
May be used with any shielded 3.5mm stereo cable up to 100'

LEDS: Blue and Red/Green

Blue: Illuminates when the device is plugged in and successfully recognised by Windows.

LED Functions: Red: Flashes when data is sent.

Green: Flashes when data is received.

*SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE. SPECIFIC WARRANTY REMEDY LIMITATIONS APPLY. CALL 1-603-456-2011 OR GO TO WWW.MADGETECH.COM FOR DETAILS.

ORDERING INFORMATION

MODEL	DESCRIPTION	PRICE (U.S.)
IFC200	USB Data Logger Interface	\$119.00

For Quantity Discounts call 603-456-2011 or email sales@madgetech.com

ASK ABOUT OUR OTHER DATA LOGGERS

Temperature
Humidity
Pressure
pH
Level
Shock
LCD Display
Pulse/Event/State
Current
Voltage
Wireless
Intrinsically Safe
Spectral Vibration
Motion